

MIDLAND CT690

NEW



VOX



BATTERY LEVEL



EMERGENCY



SCAN



CTCSS/DCS
SCAN



TOT



BUSY CHANNEL



HI/LOW
POWER



DTMF



FM RADIO



VOCAL
INDICATIONS



3 COLOURS
DISPLAY



BATTERY PACK



2 PIN
KENWOOD

AMATEUR DUAL BAND

Version: VHF/UHF
Colour: Black, Red, Yellow
Frequency: 144-146MHz
 (Exp. 136-174MHz)
 430-440MHz
 (Exp. 400-470MHz)
Output power: 5W VHF/UHF

SPECIFICATIONS:

- 50 CTCSS tones/208 DCS Codes
- 128 channels to store
- Channel spacing: 25KHz/12.5Hz
- 1750 Hz tone for repeaters
- SOS emergency function
- Operating mode: UHF-UHF, VHF-VHF and VHF-UHF
- Dual band viewing (VHF/UHF) on display and channel name
- FM radio receiver (65-108 MHz)
- Shift repeater
- Vox, Scan, Dual watch functions
- Single or group call
- Settable backlight display

- Select channel or frequency mode
- Optional viewing on display of channels number, channel number + frequency or only frequency
- TOT (time out timer)
- PTT-ID
- Setting and saving channel names
- Busy Channel lockout (BCLO) function
- Squelch adjustable to 9 levels
- Keypad lock
- Hi/Low power selection
- Frequency setting and keypad channels
- Voice indication of the function selected VOICE
- Inverted frequency function
- DTMF function, reverse
- Frequency step: 2,5/6.25/10/12.5/25 kHz
- Frequency offset: 0-69.990 MHz
- Function/channel reset
- 2-pin Kenwood accessory socket

PACKS AND CODES

Box with 1 radio, 1700mAh 7,4 V Li-ion battery pack, quick desktop charger, wall adapter, antenna, belt clip

Midland CT690 Black Code C1260

Midland CT690 Red Code C1260.01

Midland CT690 Yellow Code C1260.02

PROGRAMMING SOFTWARE PRG10

code **C974.01**

Complete with USB connection lead for PCs