

MIDLAND®

Product data sheet

01/09/2020

G13

THE SEMI-PROFESSIONAL RADIO
FOR THE MOST DISCERNING HUNTERS.



PMR446 radio

G13

The new model in the MIDLAND line dedicated to the world of hunting.

Those who practice hunting activities must be able to count on a reliable, versatile and long-lasting radio. If you think you're a hunter and you're looking for a walkie talkie that will always allow you to signal your presence in the shooting area... add the new G13 portable transceiver to your equipment.

KEY POINTS

Bright DISPLAY

To see clearly and set the radio easily.

INCREASED AUTONOMY

The supplied battery allows an autonomy of use of up to 40 hours

ABOVE-AVERAGE STURDINESS

To offer greater impact resistance, the chassis is made of aluminium

EXPANDABILITY

Extra functions programmable via software



PMR446 radio

G13

SPECIFICATIONS FEATURES

- Extended frequency band: 446.00625 – 446.19375MHz
- 16 new PMR446 channels
- 99 PMR446 channels: 16 + 83 pre-programmed
- High efficiency, 2,600mAh Li-ion battery (battery life up to 40 hours)
- High-performance loudspeaker
- LCD display with backlighting
- Aluminium chassis
- IPX4 watertightness
- LIGHT keyboard (3 keys only)
- Extra EU expandable to 5W
- RRM channel (Rete Radio Montana)
- Scrambler (via optional programming software)
- VOX, Scan, Dual Watch, Monitor
- Accessory socket: 2pin Kenwood

SOFTWARE

Compatible with the PRG-10 programming software code C974.01

COMPLIANCE

Device in compliance with the RED 2014/53/EU regulation

The reference user asks for ease of use. The G13 achieves this thanks to a touch-recognizable control layout, a large display and two main knobs:

the big one for channel change

the small one for volume control and ON/OFF.

In addition to the great sturdiness allowed by the aluminium chassis, there is the IPX4 waterproof rating.

When evaluating a transceiver, you often forget about the sound... Not with the G13: MIDLAND has provided it with a sound response of well above average quality.

The presence of the RRM (Rete Radio Montana) Channel function makes the G13 an excellent support also for those who practice hiking and trekking thanks to the possibility to automatically select the main radio frequency of Rete Radio Montana, the main emergency reporting tool.

For more information: <https://www.reteradiomontana.it/canale-8-16>

The supplied Lithium-ion battery offers ... infinite autonomy of use and the support of a fast charging circuit.

The G13 operates on PMR446 (Personal Mobile Radio) range, 446.0-446.2 MHz frequencies.

In addition to the "ready to use" features, this transceiver adds, via software, the ability to program and customize channels, enable or disable specific functions.

PACKAGING AND CODES

The package includes:

1 G13 transceiver with belt clip, 1 2,600mAh Li-Ion rechargeable battery pack, 1 wall adapter, 1 desktop charger

Code C1462



G13

ACCESSORIES

- PRG-10
Programming kit – code C974.01
- MA21-LK
PTT microphone with spiral cable – code C709.04
- MA21-XK
Microphone with PTT – code C709.06
- MA21-Lki
Microphone with L-connector – code C1306
- MA31-LK
Microphone with pneumatic earphone – code C732.04
- PB-G10 PRO
2,600mAh Li-Ion battery pack – code C1454
- BA24
Headset microphone – code C1296
- BA22
Speaker microphone with PTT and rotating clip – code C1297
- BA21
Adjustable earpiece microphone with PTT – code C1298
- BA31
Microphone with pneumatic earphone – code C1299
- BOW-M EVO K
Military headset – code C1046.03
- WA21
Bluetooth microphone headset – code C1201
- WA31
Bluetooth microphone headset with pneumatic earphone – code C1202
- WA29
Bluetooth microphone headset with headband – code C1203

